

## PA Nr. 4

Vcc 13V.....30 Volt max. 4 amper Max. input power 500mW , for SSB CW Pactor  
Output power test on 2400,0 MHz CWmode Gain >16dB

Input mW	Out & 24V	Out & 13,8V
45	3,9 W	3,1 W
57	4,5 W	3,6 W
72	5,3 W	4,15 W
90	6,3 W	4,7 W
110	7,3 W	5,4 W
135	8,4 W	6,0 W
170	9,8 W	6,5 W
210	11,2 W	7,1 W
260	12,6 W	7,7 W
320	14,5 W	8,1 W
400	16,5 W	8,5 W

Note:

Output port is not protected by circulator ! ....be careful with poor antennas VSWR

Input port --> **Overload NOT PROTECTED** Caution !

( Vcc 24V ) Sweep....

