

PA Nr. 6

Vcc 13V.....30 Volt max. 4 amper Max. input power 300mW , for SSB CW Pactor
Output power test on 2400,0 MHz CWmode Gain >19dB

Input mW	Out & 24V	Out & 13,8V
9	1,2 W	0,8 W
25	2,9 W	2,0 W
38	4,4 W	2,9 W
47	5,3 W	3,5 W
59	6,5 W	4,2 W
74	7,8 W	4,9 W
93	9,3 W	5,7 W
115	11,0 W	6,5 W
142	12,8 W	7,3 W
175	15,0 W	8,1 W
225	17,5 W	8,8 W
290	20,5 W	9,5 W

Note:

Output port is not protected by circulator !be careful with poor antennas VSWR

Input port --> **Overload NOT PROTECTED** Caution !

(Vcc 24V) Sweep....

