

PA Nr. 8

Vcc 13V.....30 Volt max. 4 amper Max. input power 700mW , for SSB CW Pactor
Output power test on 2400,0 MHz CWmode Gain >17dB

Input mW	Out W & 24V	& VSWR <1,2 Monitor Volt	Output W & 13,8V
400			
300	17,5 W	1,71 V	8,0 W
250	14,5	1,55	7,4
200	12,1	1,40	6,7
160	10,2	1,27	6,0
128	8,6	1,16	5,3
103	7,1	1,04	4,6
83	5,9	0,94	3,95
67	4,9	0,84	3,35
52	4,0	0,75	2,8
42	3,3	0,68	2,35
32	2,7	0,61	1,95

Note:

Output port is not protected by circulator !be careful with poor antennas VSWR

Input port --> **Overload NOT PROTECTED** Caution !

Heatsink necessary !!