

PA Nr. 9

Vcc 13V.....30 Volt max. 4 amper Max. input power 200mW , for SSB CW Pactor
Output power test on 2400,0 MHz CWmode Gain >22dB

Input mW	Out & 24V	Out & 13,8V
3,7	1,4 W	1,2 W
7,5	2,6 W	2,3 W
12	3,9 W	3,3 W
19	5,5 W	4,6 W
30	7,6 W	6,2 W
47	10,2 W	7,6 W
59	11,8 W	8,3 W
74	13,5 W	8,9 W
93	15,2 W	9,4 W
115	17,0 W	9,8 W
142	18,7 W	10,3 W
175	20,5 W	10,6 W
225	22,5 W	10,7 W

Note:

Output port is not protected by cirkulator !be careful with poor antennas VSWR

Input port --> **Overload NOT PROTECTED** Caution !

(Vcc 24V) Sweep....

