

PA Nr. 10

Vcc 13V.....30 Volt max. 4 amper Max. input power 200mW , for SSB CW Pactor
Output power test on 2400,0 MHz CWmode Gain >22dB

Input mW	Out & 24V	Out & 13,8V
3,7	1,6 W	1,2 W
7,5	2,9 W	2,1 W
12	4,0 W	3,0 W
19	5,7 W	4,3 W
30	8,0 W	5,5 W
47	10,7 W	7,0 W
59	12,3 W	7,7 W
74	14,0 W	8,3 W
93	15,7 W	8,8 W
115	17,5 W	9,2 W
142	19,2 W	9,5 W
175	20,6 W	10,0 W

Note:

Output port is not protected by circulator !be careful with poor antennas VSWR

Input port --> **Overload NOT PROTECTED** Caution !

(Vcc 24V) Sweep....

